

ProMax 7500EA Portable Petrol Generator

Ultimate performance for the toughest jobs.



7500

Starting Watts

6000

Running Watts

479

Displacement (cc)

7h 5min

Run Time

Specifications

Model Number

030404

Starting Watts *

7500

Running Watts **

6000

Voltage (V)

230

Frequency (Hz)

50

Run time ***

7h 5min

Outlets

2x 230V / 16 Amp, 1x 230V / 32 Amp

Alternator

Power Surge™ / AVR

Automatic Low Oil Shut Down

Yes

Voltmeter

Yes

Lubrication System

Yes

Circuit Breaker

Yes

Frame Tube Diameter (mm)

38

Weight (kg)

121

Length (cm)

89

Width (cm)

59

Height (cm)

55

Engine Brand

Vanguard™

Engine Configuration

VTwin OHV

Displacement (cc)

479

Cylinder

Cast Iron Sleeve

Fuel Tank Capacity (l)

15

Fuel Gauge

Yes

Starter

Electric Start - Key

Muffler

Quiet GenSet